

D1 Standalone

Quick Start Guide

09/01/2009

Before Turning On The System

- Please install **SATA HDDs** in the Hard Disk bracket, and **DVD Writer** in the DVD bracket. **(Sec. 4.1, 4.5)**
- Please set the NTSC/PAL Selector Switch according to the local TV system. (Sec. 4.2)
- Please refer to Sec.4.5,4.6 for all connections.

After Turning On The System

- Please wait for about 40 seconds for the system to start up.
- **Please login the system (Sec. 7.1), and then physically format the HDDs (Sec. 7.7.6.1). (Please note that the HDDs cannot be used for recording if they are not formatted yet.)**
- Please refer to Sec. 7.7.8 and Appendix A to set the time zone of the system.
- Please refer to Section 5.1 to enter text.
- Please refer to Section 5.2 for all basic operations.
- Please refer to Section 7.7 to setup the system correctly, esp. Section 7.7.8 for Time Zone, DST & Language.
- Please refer to Chapter 10 to search, playback, and archive the recorded video/audio.
- Please refer to Sec. 4.2, 7.7.10, and Chapter 11 for remote access via internet or intranet.
- Please refer to Sec. 4.2, 7.7.1, 7.7.9, and Chapter 8 to control the PTZ cameras correctly.
- Please refer to Sec. 4.2, 4.6, 7.7.9, to use the keyboard controller or terminal correctly.
- Please refer to Sec. 4.2, 4.6, 7.7.9, 4.5, 10.6, to use GPS function correctly.
- Please refer to Sec. 4.2, 4.6, 7.7.9, 4.5, 10.5, 10.6, and 10.10 to use POS function correctly.
- Please refer to Appendix C,D for the estimated recording time.
- Please refer to Chapter 13 for the Protocol Converter for Multiple POS.

Special Note

- **For internal DVD, please do not block the tray from ejecting while the DVD is in backup process. Blocking the tray from ejecting may damage the DVD writer.**


Login The System

- Login / Logout : **MENU**->Login/Logout


Setup The System


- Format HDD : **MENU**->Setup->HDD->Format HDD (**MODE**)->Physical Format (**CALL**)
- Change Time Zone, Language : **MENU**->Setup->System->Time Zone, Language
- Setup PTZ, Keyboard, POS, GPS : **MENU**->Setup->RS-232/422/485->Device Type, ..
- Setup Network : **MENU**->Setup->Network->Net Type, Static IP or PPPoE, ..
- Change Network Port : **MENU**->Setup->Network->Adv.


Basic Operations

- Change Split Window :  +/-
- Change Live / Playback mode : **MODE**
- Move Focus : ▲, ▼, ◀, ▶
- Connect / Disconnect Backup Device : **MENU**->Backup Device->Connect / Disconnect





- **Search/Playback/Archive** : **Search**->Search By Time, Smart Search, ..

- **Search By Time** : Select the start time & video type, and
 - Play : ▶/||, **MODE**, **Search**
 - Backup : 

- **Search By Event** : Select and move to the event, and
 - Play : ▶/||
 - Backup : 

- **Smart Search** : Select the camera, area covered by the motion occurred, and start/end time, and press **SEARCH** or **MODE** to search the matched files. Select and move to the file, and
 - Play : ▶/||
 - Backup : 

- **Search Archived File** : Connect Backup Device (by pressing **ENTER** in Device), and select and move to the file, and
 - Play : ▶/||



- **POS Search** : Select the camera, keyword, and start/end time, and press **SEARCH** or **MODE** to search the matched files. Select and move to the file, and
 - Play : 
 - Backup : 
- **Backup** : Connect Backup Device (by pressing **ENTER** in Device), and select cameras, end time, etc., and
 - Backup : 
 - Stop Backup : 

Note: For internal DVD, please do not block the tray from ejecting while the DVD is in backup process. Blocking the tray from ejecting may damage the DVD writer.

Remote Access -> Before Logging On

- Set the domain name or IP address of the DVR as **trusted web site** in your I.E., and the **(https:) server verification** for trusted web site as **unchecked** (Tools->Options->Security in I.E.). For I.E. 7, please set the **Security level for this zone to Low**.
- If the PC has used I.E. to access earlier software version of DVR, please go to Tools->Options->General in your I.E. to **delete "Temporary Internet files" and all offline contents**.

Remote Access -> Operations

- Please note that the PC user must have system administrator password for the PC; otherwise, the process will fail, and an error dialog will be shown.
- Add More DVRs : Click on  to call up Setup dialog. Add more DVRs in the DVR list.
- Select DVR : Click on .
- Context Menu : Right-click in the video window to call up Context Menu.